# WACO DIGITAL EARTH RESISTANCE TESTER

# **Digital Earth Tester**

## **Application**

'WACO' Digital Earth Resistance Tester is designed to measure the resistance if earth used in power circuit, Telecommunications, Railway Electrification, Domestic and Industrial electrical installations. The tester measures directly the resistance of the earth and also measure the ground resistivity. The study, elegant and compact body makes the instrument portable, easy to use, Hand-held instrument.

#### **Features**

- Rugged ABS body
- Easy to use hand held meter
- Ni-cd Re- chargeable Cells output 12V, 1A.
- Confirms to ISS: 9223/1979
- Four terminals (To measure earth resistance as well as specific soil resistivity}
- Lo-Bat or Δ indication appears on Display indicating that the indicating the the cells (batteri es) have gone down, which can be recharged by connecting to 230V, 50 Hz AC mains supply through charging cord provided with the instrument

## **Technical Details**

Display : 31/2 Digits, LCD

Dimensions (in mm) : 172 x 98 x 38 (Approx.)

Weight 575 gm (Approx.)





#### **Accessories**

Standard : (i) Carrying Case Accessories (ii) Charging Cord (iii) Instruction Manual

: • 4 Nos. M. S. Spike (18 Inch Length) • 1 Nos. Hammer • 4 Nos. Cable (25 feet) • 1 Nos. Screwdriver, all packed in one Optional earth testing kit bag specially designed for Waco Earth Testers.

**Accessories** 

(at extra cost)

# **Dual Ranges**

(C) 0 -20 -2000 OHM (a) 0 - 10 - 1000 OHM (b) 0 - 5 - 500 OHM

#### Guarantee

Guaranteed for 12 (twelve) months against any manufacturing defects